OSRAM

ORIGINAL - PSX PS24W

OSRAM spare parts



OSRAM spare parts

Discover our ORIGINAL PSX lamps. The spare parts are signal lamp types for different applications. They provide a high and constant luminous flux.

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
•	

General Product Information

Global order reference	5202
------------------------	------


Electrical Data

Power input	25 W
Nominal voltage	12.0 V
Nominal wattage	24 W
Test voltage	13.5 V

Photometric Data

Nominal luminous flux	500 lm
Luminous flux tolerance	+10 %; -20 %

Physical Attributes & Dimensions



Diameter	18.5 mm
Diameter	18.5 mm
Product weight	9.60 g
Length	46.7 mm
Lamp base	PG20-3

Lifetime Data

Lifespan B3	500 hr
Lifespan Tc	1000 hr

Capabilities

Technology	AUX 1)
------------	--------

¹⁾ Auxiliary signal lamp

Certificates & standards

ECE category	PS24W
LCL category	1 32 111

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)				
Primary article identifier 4052899600584				
Candidate list substance 1	No declarable substances contained			
Declaration no. in SCIP database	No declarable substances contained			

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4052899600584	ORIGINAL - PSX PS24W	FS ECO 1	34 mm x 34 mm x 58 mm	0.07 dm ³	13.00 g
4052899600591	ORIGINAL - PSX PS24W	Shipping carton box 100	356 mm x 186 mm x 129 mm	8.54 dm ³	1472.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

File



User instruction
GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















OSRAM