

# PRODUCT DATASHEET SMART+ WIFI NIGHTLIGHT PLUG EU

SMART+ NIGHTLIGHT Plug | Nightlight integrated plug with smart socket to control non smart devices with WiFi technology



# Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- Nightlight as an orientation light or safety light for children's rooms, stairs, or bedrooms

# **Product benefits**

- Integrates conventional electric equipment into compatible smart home systems
- Nightlight as an orientation light or safety light at night or in dark area
- Nightlight separately controllable and dimmable
- Simple connection of electric devices via standard socket
- Monitors energy usage of connected devices and tracks the energy consumption
- Enables switching of conventional light sources and other electric devices

## **Product features**

- Controllable via LEDVANCE SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Controllable via LEDVANCE SMART+ WiFi Remote Controller
- High switching power: up to 3,680 W / 16 A
- Network protocol: WiFi
- Energy meter




- Nightlight integrated with warm white and dimmable
- Scheduling

## **TECHNICAL DATA**

# **Electrical data**

Nominal voltage	230 V
Mains frequency	50 Hz

## **Dimensions & Weight**



Product weight	120.00 g
Length	60 mm
Width	60 mm
Height	84 mm

## Lifespan

Number of switching cycles	100000
----------------------------	--------

# Colors & materials

Product color	White
Body material	Plastic

# Temperatures & operating conditions

## Capabilities

## **Certificates & Standards**

Protection class	1
Type of protection	IP20

# **EQUIPMENT / ACCESSORIES**

- For control via LEDVANCE SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)

### Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Plug, after use in order to avoid them being accidentally switched on.
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Plug in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (max. 16 A).

#### **DOWNLOAD DATA**

	Documents and certificates
POF	Installation guide
POF	Declarations Of Conformity CE

## LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075570993	Folding box 1	61 mm x 96 mm x 154 mm	188.00 g	0.90 dm <sup>3</sup>
4058075571006	Shipping box 4	211 mm x 167 mm x 141 mm	900.00 g	4.97 dm <sup>3</sup>

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### **References / Links**

- Further information and frequently asked questions (FAQs) at www.ledvance.com/consumer/smart/faq

## DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.