OSRAM

ORIGINAL - FESTOON -

Original spare part





The cost-effective original spare parts

The ORIGINAL festoon lamps with OSRAM's reliable OEM quality can be used as original spare parts for a wide range of festoon lamps. The typical application areas of the lamps are number plate and side position lights as well as interior lighting and reading lights.

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference 6486X	
------------------------------	--


Electrical Data

Power input	6 W
Nominal voltage	12.0 V
Nominal wattage	6 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometric Data

Nominal luminous flux	85 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions



Diameter	11.0 mm
Diameter	11.0 mm
Product weight	2.50 g
Length	36.0 mm
Lamp base	SV8.5-8

Lifetime Data

Lifespan B3	350 hr
Lifespan Tc	600 hr

Capabilities

Certificates & standards

ECE category	-
--------------	---

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)			
Primary article identifier	4008321007803 4008321094292		
Candidate list substance 1	No declarable substances contained		
Declaration no. in SCIP database No declarable substances contained			

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321094292	OSRA6486X	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094292	ORIGINAL FESTOON 6486X	Unpacked 1	36 mm x 11 mm x 11 mm	0.00 dm ³	3.00 g
4008321094315	ORIGINAL FESTOON 6486X	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm ³	245.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

File



User instruction GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















